

MODEL : K275PO



Image provided for illustrative purposes only

Power Rating		
Standby power LTP	kVA	275,0
Prime power PRP	kVA	250,0

Main Features		
Frequency	Hz	50
Voltage	V	400/230V
Power factor	cos ϕ	0,8
Phase and connection		3

Main Specifications		
Engine Make & Model	Perkins	1506A-E88TAG3
Speed Governor		Electronic
Alternator Make & Model	Mecc Alte	ECO38-1LN/4
Fuel Tank (ltrs) / Autonomy @75% load (hrs)	636	15
Noise Level - dB(A)@7mt		0
Dimensions	L x W x H (mm)	0
Weight	Kg	0

General Structure

BASE FRAME MADE OF WELDED STEEL PROFILE, COMPLETE WITH:

- Anti-vibration mountings properly sized
- Welded or Screwed support legs.

PLASTIC FUEL TANK WITH THE FOLLOWING COMPONENT:

- Filler neck
- Air breather (ventilation pipe)
- Minimum fuel level sensor

MANUAL OIL DRAININ PUMP:

- Oil draining facilities

ENGINE COMPLETE WITH:

- Battery
- Liquids (no fuel)

PROTECTIONS:

- Moving and rotating parts protection against accidental contacts

LIFTING:

- Lifting points frame structure.

EXHAUST (STANDARD):

- Industrial silencer (loose)

TECHNICAL DATA SHEET

Engine		
Brand		Perkins
Model		1506A-E88TAG3
Speed Governor		Electronic
Max power PRP	kW	222
R.P.M.		1500
Cylinders		6 in line
Displacement	cm ³	8800
Fuel consumption at 75% of load	l/h	41,6
Cooling System		Water
Aspiration		Turbocharged

ALTERNATOR		
Brand		Mecc Alte
Model		ECO38-1LN/4
Pole		4
Stator/rotator insulation		H
Protection level	IP	21

PHYSICAL CHARACTERISTICS		
Integrated fuel tank	LTR	636
Lead acid batteries		12V155AH
Dimensions	L x W x H (mm)	0
Weight	Kg	0

Noise Level dB(A) LWA		
Guaranteed Noise Level	dB(A) LWA	0
Noise Pressure Level	@ 7 mt	0

ACP - Automatic control panel

Mounted on the genset, complete with digital control unit AC03 for monitoring, control and protection of the generating set, protected through door with lockable handle.

COMMANDS AND OTHERS

- Four operation modes: OFF - Manual starting - Automatic starting - Automatic test.
- Push-button for forcing Mains contactor or Genset contactor.
- Push-buttons: start/stop, fault reset, up/down/page/enter selection.
- Remote starting availability.
- DC system disconnection switch.
- Acoustic alarm.
- Automatic battery charger.
- RS232 Communication port.
- Settable PASSWORD for protection level.

ALARM PROTECTION

- Engine protection: low fuel level, low oil pressure, high engine temperature.
- Genset protection: under/over voltage, overload, under/over frequency, starting failure, under/over battery voltage

SHUT DOWN PROTECTION

- Engine protection: low fuel level, low oil pressure, high engine temperature,
- Genset protection: under/over voltage, overload, under/over battery voltage, battery charger failure.
- Circuit breaker protection: III poles.
- Earth Fault included in the control unit.

OTHERS PROTECTION

- Emergency stop button.
- Panel protected through door with lockable handle.

OUTPUT PANEL ACP

Plinth row for connection from ACP to LTS panel.
 External Terminal Board (ETB) Standard



LTS - LOAD TRANSFER SWITCH - Accessories ACP

Nominal Current	A	400
Width (W)	mm	800
Height (H)	mm	600
Depth (D)	mm	300